

**MODEL NUMBER**

**ADC-SVR122E**

**SPECIFICATIONS**

**RECORDING CHANNELS**

Up to 8 Cameras

**COMPATIBLE CAMERAS**

All available cameras

**TRANSCODED PLAYBACK**

MPEG4, H.264

**SPEED CONTROL**

1x, 4x, 8x, 16x, 32x, 64x

**HDD BAY**

1 Bay, 500GB or 1TB

**ETHERNET CONNECTION**

10Base-T/100BaseTX (RJ45)

**COOLING**

Fanless Thermal Heat Sink

**DIMENSIONS**

3.5 x 3.5 x 5.8" (88 x 88 x 146.7 mm)

**OPERATING TEMPERATURE**

32°-104°F (0°-40°C)

**STORAGE TEMPERATURE**

-13° to 158°F (-25° to 70°C)

**OPERATING HUMIDITY**

20%-95% RH (non-condensing)

**POWER ADAPTOR**

12V DC, 18W



# Stream Video Recorder

Designed specifically to work with the Alarm.com hosted video service, the ADC-SVR122E Stream Video Recorder provides a 24x7 professional local video storage solution. With the Stream Video Recorder, you can connect up to eight Alarm.com video cameras for continuous recording.

## Service Packages

- Pro Video + Add-On
- Pro Video with Analytics 3000 + Add-On

## Included Accessories

- Power Adapter
- Quick Installation Guide

## LED GUIDE

	LED STATUS	DESCRIPTION
<b>STATUS LED</b> <i>Front of SVR</i>	Solid Green	Local network and Internet connection
	Flashing Green	Local connection only, no Internet
	Solid Red	Cameras not recording or hard drive error. Check LEDs on back of SVR.
	Flashing Red	SVR is booting
	Flashing Green & Red	Factory Reset
<b>SVR HARD DRIVE</b> <i>Back of SVR</i>	Solid Green	SVR hard drive is operating normally
	Flashing Green	Hard drive is full. Oldest footage is being deleted
	Solid Red	Hard drive configuration error
<b>CAMERAS 1-8</b> <i>Back of SVR</i>	Solid Green	Camera is connected and recording
	Flashing Green	Camera connected and recording paused
	Flashing Red	Camera disconnected